

Single-phase Motor Type	ASR 100LB6	6pole
Motor technology	Capacitor start- capacitor run motor	
Start capacitor disconnecting	Centrifugal switch inside motor enclosure	
Area	Safe Area	
Environmental Conditions	-20°C to +40°C, up to 1000 metres above sea level	
Rated Voltage	230V 50Hz	
Output at 50Hz	1.5 kW	
Frame Size	100L Aluminium	
Speed at 50Hz	890 rpm	
Current at 230V 50Hz	10.6A	
Efficiency Class	n/a	
Efficiency at 50Hz	65.0%	
Power factor (cos fi)	0.95	
Rated Torque at 50Hz	16.1 Nm	
Duty Cycle	S1- Continuous duty	
Starting Current Ratio	4.20	
Starting Torque Ratio	1.90	
Breakdown Torque Ratio	1.90	
Internal Protection / Cooling	IP55 / IC411 (TEFC)	
Insulation Class	class F/B	
Standard Mountings	B3, B5, B3/B5, B14A, B3/B14A, B14B, B3/B14B	
Run capacitor	45µF/450V	
Start capacitor	156µF/280V	
Weight	21. kg	
Bearing DE/NDE	6206-2Z / 6206-2Z	
Bearing lubrication	Bearings lubricated for life with lithium based grease	
Wiring Diagram		

Country of origin Bulgaria

Please note that the same electrical design of Single-phase motor cannot be used for 50Hz and 60Hz.
 *Unloaded or underloaded single-phase motors produce higher level of noise than fully loaded motors.